

XH-3568D3-GPIO索引值

名称	I0	描述	io口说明
USB_HOST_PWREN_H_GPIO4_B1	GPIO4_B1	J7 USB供电控制	sys/class/gpio/gpio137/value
USB_HOST_PWREN_H_GPIO4_A7	GPIO4_A7	J26 USB供电控制	sys/class/gpio/gpio135/value
USB_HOST_PWREN_H_GPIO4_B0	GPIO4_B0	J19 USB供电控制	sys/class/gpio/gpio136/value
USB_HOST_PWREN_H_GPIO4_A6	GPIO4_A6	J2 USB供电控制	sys/class/gpio/gpio134/value
USB_HOST_PWREN_H_GPIO0_A6	GPIO0_A6	J12 USB供电控制	sys/class/gpio/gpio6/value
USB_HOST_PWREN_H_GPIO4_A5	GPIO4_A5	J15 USB供电控制	sys/class/gpio/gpio133/value
LED1_RED_GPIO2_D1	GPIO3_C6	补光灯红色控制	sys/devices/platform/misc_power_en/led1_red
LED1_BLUE_GPIO2_D2	GPIO3_C7	补光灯蓝色控制	sys/devices/platform/misc_power_en/led1_blue
LED1_GREEN_GPIO2_D0	GPIO3_D0	补光灯绿色控制	sys/devices/platform/misc_power_en/led1_green
RECLY_CT1_GPIO2_C7	GPIO2_D4	继电器控制	sys/devices/platform/misc_power_en/relay_ctl
GPIO口	GPIO2_B7	GPIO控制I01	sys/class/gpio/gpio143/value
GPIO口	GPIO2_C0	GPIO控制I02	sys/class/gpio/gpio144/value
GPIO口	GPIO2_D2	GPIO控制I03	sys/class/gpio/gpio154/value
GPIO口	GPIO2_C3	GPIO控制I04	sys/class/gpio/gpio147/value

